

Dual Polarity DC-DC Converter Integrated Grid-tied Single-Phase Transformer Less Inverter for Solar Application

S. S. Ghosh¹, K. S. Nathan¹, Y. P. Siwakoti² and T Long¹

1: Department of Engineering -University of Cambridge, United Kingdom
ssg39@cam.ac.uk, ksn26@cam.ac.uk, tl322@cam.ac.uk

2 Faculty of Engineering and IT, University of Technology Sydney, Australia,
Yam.Siwakoti@uts.edu.au

Index Terms—Bipolar DC-AC Converter, Ćuk SEPIC Converter, Solar Application, Pulsed Width Modulation

Abstract—This paper proposes a novel single-phase transformer-less inverter, using the principle of Combined Ćuk SEPIC (CCS) converter for grid-connected Photovoltaic (PV) systems. The new inverter has a common ground between the grid and the PV source, which helps to eliminate the leakage current for the grid-connected PV application. Unlike common ground type charge pump based transformer-less inverter, this topology eliminates inrush current and hence reduces the current stress on the components. The CCS allows voltage control with both step-up and step-down abilities, along with more robustness against solar panel side fault. Further, application of wide band-gap devices, such as SiC MOSFETs allow higher switching frequency to be achieved, and thus reduction of the passive components. A novel switching strategy, proposed here allows current in both directions, positive and negative (to the load/grid or from the load/grid, for reactive loads), making the converter suitable for grid connection (unity power factor), as well as stand-alone operation. The proposed concept has been discussed in detail, along with simulation results. Finally, a prototype hardware has been fabricated and the experimental results are reported.

I. INTRODUCTION

Grid-connected photovoltaic systems (PV), particularly low power single-phase systems (up to 5kw) are becoming more common worldwide, due to declining PV price, government incentives and advancement in power electronics and technology [1]. To date, the PFC boost converter, coupled with H-bridge and transformer has been the most popular topology for PV systems. Besides providing the additional capability to adjusting voltage level, the inherent galvanic isolation blocks common mode (CM) current and limits the fault current. However, , due to weight and volume of the line frequency transformer, different topologies [2], [3] have been proposed to avoid them without losing the main benefit of blocking CM current. It has been previously reported, by using a virtual DC bus [4], the common ground connection can be achieved, which diverts CM current.

In this paper, a novel converter topology has been proposed based on dual polarity DC-DCconverter, which creates separate positive and negative virtual DC bus, thus allowing the




Fig. 1. Converter Topology

common ground connection of the Solar panel with the grid. The dual polarity DC-DCconverter allows more flexibilities for voltage control with both step-up and step-down abilities, along with more robustness against solar panel side fault.

The next section details the converter topology and operating principles, along with pulse width modulation (PWM) strategy of different switches in the converter. The proposed converter has been investigated with simulation studies, using MATLAB-SIMULINK and PLECS, and the results are reported. Finally, a laboratory prototype has been developed and experimental results are presented to validate the concept.

II. CONVERTER TOPOLOGY AND OPERATION

The circuit schematic of the converter is shown in Fig 1. The converter can be analysed as a two-part system, consisting of a Combined Ćuk SEPIC (CCS) converter [5] along with a bipolar DC to single phase AC converter. The CCS converter generates a bipolar DC output, which is referred as virtual DC bus. The switching node of the Ćuk and SEPIC converter is unified by the switch $S1$. The Ćuk converter generates a negative voltage with respect to the common ground node G , at node N . Similarly the SEPIC converter creates the positive voltage output at node P with respect to the ground. The output of the Ćuk and the SEPIC converter is related to input




Fig. 2. Converter Operation Modes

DC voltage as below:

$$V_{C_{uk}} = -V_{in} \frac{d}{1-d} \quad (1)$$

$$V_{SEPIC} = V_{in} \frac{d}{1-d} \quad (2)$$

Where V_{in} is the input DC voltage, and d is the duty ratio of the switch. The dual polarity output generated by this CCS converter, between nodes P , N and G , is fed to the bipolar DC to single phase AC converter consisting four switches S_p , S_n , S_{zp} , and S_{zn} , which produces an AC output. It can be observed, the load neutral point, node G is common to the

source ground, thus allowing a common ground connection which eliminates the Common Mode (CM) leakage current.

Switch S_p of the Bipolar DC-AC converter is switched in sine PWM during the positive half cycle. During switch-on period – positive -active, the circuit path is shown in Fig 2- Positive Voltage active. The antiparallel diode with the MOSFET allows the current path for both the direction. When the switch S_p is turned off, the zero state switches S_{zp} and S_{zn} , need to be turned on, to allow the current path for the load. Depending on the direction of the current, it can take either of the two paths. For the current to the load (positive direction) the path is completed by the antiparallel diode of the switch S_{zn} and the MOSFET S_{zp} as shown in Fig. 2. For negative current, current from the load or grid side, the path is completed by the S_{zn} and the antiparallel diode of S_{zp} , also shown in Fig. 2. It should be noted, while the switch S_{zp} can be kept on during the positive half cycle of voltage, as the antiparallel diode of S_{zn} blocks the path for current. However, during the switch-on period of S_p , S_{zn} must remain turned off, otherwise, it will lead to short-circuiting across the nodes P and G . This will require switching only S_p and S_{zn} in a complementary fashion, during positive half cycle. This strategy will reduce switching loss of the converter, as S_{zp} is not switched, although it provides current path as necessary. However, to ensure there is no short-circuit, a dead time has to be inserted between the gate pulses of S_p and S_{zn} . During this dead time period, when neither of the switches is on, in case of positive current, the path is completed by S_{zp} and anti-parallel diode of S_{zn} . However, if the load/ grid current is negative during a particular switching, the path is completed by antiparallel diode of S_p and feeding back to the positive DC bus (Node P) capacitor C_{pos} .




Fig. 3. PWM pulses of different switches

Similarly, during the negative half-cycle of voltage, the negative bus switch S_n is switched in Sine - PWM fashion, shown in Fig. 2 - negative active. To provide the circulating current path, during off period, similar to positive half cycle, S_{zp} and S_{zn} are switched, and the operation modes are same as before. During this negative half -cycle period, S_{zn} can be kept on, while S_{zp} being switched complementarily with S_n . Similar to positive half-cycle, here too, dead time should be inserted between the pulses of S_n and S_{zp} . Finally, the output of the Bipolar-DC to single phase AC converter is fed to an LC filter, before connecting to the load (in case of stand-alone operation) or grid.

The PWM pulses for the switches in the converter, S_1 , S_p , S_n , S_{zp} , and S_{zn} is shown in Fig. 3. The x-axis (time) is not to scale, to show the sine - PWM pattern of the switches of the AC converter. S_1 is switched at high frequency, 100kHz to keep the size of the passive components of the CCS small. Further, increasing the switching frequency of S_p , S_n , S_{zp} , and S_{zn} will allow redirection in size of the filter components L_f and C_f .

III. SIMULATION RESULTS

TABLE I
CONVERTER AND COMPONENT SIZE AND RATING

Component	Size
Converter	1kW
Input (Nominal)	360V
Input Range	290V to 400V
Output	240V (RMS), 50Hz
L_{in}	546 μ H
$L_{SEPIC}, L_{\dot{C}uk}$	890 μ H
C_{SEPIC}	1.19 μ F
$C_{\dot{C}uk}$	0.47 μ F
C_{pos}, C_{neg}	500 μ F
L_f	330 μ H
C_f	1 μ F

Having discussed the topology of the converter, and operation principle, a MATLAB -SIMULINK and PLECS based simulation model has been developed to study the converter in details. The specification of the simulated converter specification along with the component size is given in Table I.

The converter has been simulated with nominal 360V as well as the limit input voltages (290V and 400V). $\dot{C}uk$ converter generates a negative voltage between nodes N and G . The duty ratio of S_1 has been controlled in a closed loop to maintain the desired voltage across capacitor C_{pos} and C_{neg} , as the load of both the $\dot{C}uk$ and the SEPIC converter changes from zero to peak in each negative half cycle and positive half cycle respectively. Further, the closed loop operation takes care of no-load operation of the $\dot{C}uk$ converter during the positive half cycle, otherwise which can lead to voltage build-up across C_{neg} . Further, the bipolar DC-AC converter also takes feedback of DC bus voltage level, to generate a 240V RMS, 50Hz output.

The simulation results for input voltage 290V, where input current will be maximum, are presented in Fig. 4. It can be

observed, the closed loop controller is working to maintain the DC bus voltage at $\pm 350V$. However, due to the variation of load in 50Hz sinusoidal fashion, there is a voltage ripple of 50Hz frequency, on top of smaller variation at switching frequency of S_1 . However, the net peak to peak variation is kept less than 5% of the rated bus voltage for both $\dot{C}uk$ and SEPIC converter.

It can be further observed, the higher switching frequency of the bipolar DC-AC converter, along with the filter, generates a sinusoidal voltage output, with very less THD content. THD was measured to be 0.8%. The drain-source voltage of different switches was measured too. The maximum voltage across switches S_p and S_n goes up-to 700V, which is the total voltage across positive and negative DC nodes P and N respectively. However, the novel switching strategy discussed in the previous section results in lesser voltage stress across switches S_{zp} and S_{zn} as only two of the four switches of the bipolar DC-AC converter is switched at the PWM frequency. The maximum voltage stress across these two switches are same as individual virtual DC bus voltage levels, not the total.

IV. EXPERIMENTAL VALIDATION

A prototype has been developed for experimental validation of the proposed converter. To achieve a high switching frequency, particularly for the switch S_1 a Sic MOSFET (CREE C3M0075120K) has been used, as this offers capability to switch at frequency up to 500kHz and voltage rating up to 1.2kV. For rated operation of the converter (240V RMS output), the voltage stress across the switches S_p and S_n is shown to be 700V for $\pm 350V$ virtual DC bus level. Further, as discussed in the previous section, ability to switch the bipolar DC- AC converter at a higher frequency, allows the lower size of the filter. Hence the same MOSFET has been used there too. Silicon Carbide Schottky Diodes(STPSC20H12) has been used for the CCS converter. A TI 28069M launchpad DSP controller has been used as the PWM sources.

To maintain modularity, and easy debugging and probing during prototype building, the converter was also made as two-part system. The first part consists CCS converter and generates a bipolar DC output from the unipolar DC input. The other converter is designed to take in the bipolar output of the previous converter as its input, and generate single-phase AC, which can be connected to grid or operated in standalone mode. Fig. 5(a) shows the laboratory prototype of CCS converter. Fig. 5(b) and (c) shows the developed bipolar DC-AC converter. Further, the inductors for CCS converter too were built in the laboratory, using nanocrystalline core, as shown in Fig. 5(d)

Experimental results were taken at input DC voltage of 75V and a 470 Ω resistive load. Switching frequency of S_1 was kept at 100kHz. The bipolar DC-AC converter switches S_p , S_n , S_{zp} , and S_{zn} were switched at 20kHz. The experimental results of the CCS converter is shown in Fig. 6(a). The duty ratio of the switch S_1 is set to 0.5. For a 75V input, 6(a) shows $\pm 75V$ across positive and negative DC bus in channel 1 and 4 respectively. Fig 6(b) shows the output of the bipolar DC-AC

converter before and after the filter. It can be observed, similar to simulation result the THD present in the output AC is very less. Further, the drain to source voltages across the different switches of the bipolar DC-AC converter was measured, and shown in Fig. 7. In line with the simulation result, for a $\pm 75V$ virtual DC bus, V_{DS} across the switches S_p and S_n go to 150V, whereas, the voltage across the switches S_{zp} and S_{zn} remain 75V.

V. CONCLUSIONS

In this paper, a novel converter topology, based on CCS converter for solar application, has been presented. The CCS converter creates virtual bipolar DC bus, and a bipolar DC-AC converter feeds to AC. Further, a novel PWM strategy for the bipolar DC-AC converter has been reported, which requires only two switches to be switched at high-frequency in either of the positive or negative half cycles. Moreover, the converter allows common ground connection between the input DC source and AC. This feature is particularly helpful for blocking CM current in the grid-connected solar converters. The proposed converter topology along with PWM strategy has been discussed in detail. Further, both simulation and experimental results of the fabricated hardware laboratory prototype has been reported in detail to validate the concept. In this paper, only open loop experimental results are presented. Closed loop control of the converter, along with the grid connection of the AC output of the converter will be presented in future work.

ACKNOWLEDGEMENTS

The authors would like to express their sincere thanks to the Commonwealth Scholarship Commission UK, Cambridge Trust and the Isaac Newton Trust for their kind support to fund this research. The authors would also like to thank Prabhat Tripathi and Xinru Li for assisting with the inductor design and fabrication of the designed hardware.

REFERENCES

- [1] [1] G. Petrone, G. Spagnuolo, R. Teodorescu, M. Veerachary, and M. Vitelli, "Reliability Issues in Photovoltaic Power Processing Systems," IEEE Trans. Ind. Electron., vol. 55, no. 7, pp. 2569–2580, Jul. 2008.
- [2] [2] M. Xu, L. Zhang, Y. Xing, and L. Feng, "A Novel H6-type Transformerless Inverter for Grid-Connected Photovoltaic Application," in Proc. IEEE Ind. Electron. Appl., pp. 58–63, Jul. 2012.
- [3] [3] B. Yang, W. Li, Y. Gu, W. Cui, and X. He, "Improved Transformerless Inverter with Common-Mode Leakage Current Elimination for a Photovoltaic Grid-Connected Power System," IEEE Trans. Power Electron., vol. 27, no. 2, pp. 752–762, Feb. 2012.
- [4] [4] Y. Gu, W. Li, Y. Zhao, B. Yang, C. Li and X. He, "Transformerless Inverter with Virtual DC Bus Concept for Cost-Effective Grid-Connected PV Power Systems," IEEE Trans. Power Electron., vol. 28, no. 2, pp. 793–805, Feb. 2013.
- [5] [5] Ferrera, Maria Bella, et al. "A converter for bipolar DC link based on SEPIC-Cuk combination." IEEE transactions on Power Electronics 30.12 (2015): 6483–6487.







Fig. 4. Simulation Results



(a)



(c)




(b)




(d)

Fig. 5. Fabricated Converter (a) Combined Ćuk Sepic Converter (b) Bipolar DC-Single Phase AC Converter - Gate Drive Side (c) Bipolar DC-Single Phase AC Converter - Power Switches (d) Used Inductors




(a)




(b)

Fig. 6. Experimental Results: (a) CCS Converter: Ch1: V_{DC+} Ch2: V_{ds} across S_1 Ch3: Input Current Ch4: V_{DC-} (b) Output: Ch4: Out Put AC, Ch2: Output before filter



(a)



(b)

Fig. 7. V_{ds} across switches of bipolar DC-AC Converter (a) V_{ds} across S_p [ch4] and S_{zp} [ch2] (b) V_{ds} across S_{np} [ch4] and S_n [ch2]